

BMT116  
**MİKRODENETLEYİCİLER**

**11.HAFTA**

**GAMA MESLEK YÜKSEKOKULU**  
**ÖĞR.GÖR.MEHMET DURSUN**

;PORTA YA BAGLI OLAN BUTONLARDAN HANGİSİNE BASILIRSA O PORTA KARSILIK GELECEK  
;SAYININ 7 SEGMENT DISPLAY DE GÖSTERİLMESİ

LIST P=16F84

INCLUDE"P16F84.INC" ;file include

BSF STATUS,RP0 ;Change page1

MOVLW H'1F'

MOVWF TRISA ;PORTA ALL input

CLRF TRISB ;TRISB=0 PORTB all output

BCF STATUS,RP0 ;Change page0

	CLRF	PORTB	;Clear PORTB
MAIN	BTFSC	PORTA,0	;PA0 ON?(PA0 << Low)
	GOTO	SKIP1	;PA0 OFF >> SKIP1(PA0 << High)
	MOVLW	B'00111111'	;PA0 ON >> 7segment >> 0
	MOVWF	PORTB	
	GOTO	MAIN	
SKIP1	BTFSC	PORTA,1	;PA1 ON?
	GOTO	SKIP2	;PA1 OFF >> SKIP2
	MOVLW	B'00000110'	;PA1 ON >> 7segment >> 1

	MOVWF	PORTB	
	GOTO	MAIN	
SKIP2	BTFSC	PORTA,2	;PA2 ON?
	GOTO	SKIP3	;PA2 OFF >> SKIP3
	MOVLW	B'01011011'	;PA2 ON >> 7segment >> 2
	MOVWF	PORTB	;PORTB >> 0
	GOTO	MAIN	
SKIP3	BTFSC	PORTA,3	;PA3 ON?
	GOTO	SKIP4	;PA3 OFF >> SKIP4

```
MOVLW    B'01001111'    ;PA3 ON >> 7segment >> 3  
  
MOVWF    PORTB          ;PORTB >> 0  
  
GOTO     MAIN  
  
SKIP4    MOVLW    B'01110001'    ;PA3 ON >> 7segment >> 3  
  
MOVWF    PORTB          ;PORTB >> 0  
  
GOTO     MAIN  
  
END
```

## PROGRAMIN ISIS DE SİMÜLASYONU

